

P-Channel Enhancement Mode MOSFETs

Device	BV_{DSS} (V)	$R_{DS(ON)}$ max (Ω)	$I_{D(ON)}$ min (A)	C_{ISS} max (pF)	$V_{GS(TH)}$ max (V)	Package Options	Application Notes
LP0701	-16.5	1.5	-1.25	250	-1.0	3-Lead TO-92 (N3)	AN-D14
						8-Lead SOIC (LG)	-
TP0604	-40	2.0	-2.0	150	-2.4	3-Lead TO-92 (N3)	-
						20-Lead SOIC (WG)	
TP0606	-60	3.5	-1.5	150	-2.4	3-Lead TO-92 (N3)	-
TP0610T	-60	10	-0.05	60	-2.4	3-Lead SOT-23 (T)	-
TP0620	-200	12	-0.75	150	-2.4	3-Lead TO-92 (N3)	AN-H53
TP2104	-40	6.0	-0.6	60	-2.0	3-Lead SOT-23 (K1)	-
						3-Lead TO-92 (N3)	
TP2424	-240	8.0	-0.8	200	-2.4	3-Lead SOT-89 (N8)	-
TP2435	-350	15	-0.8	200	-2.4	3-Lead SOT-89 (N8)	-
TP2502	-20	2.0	-2.0	125	-2.4	3-Lead SOT-89 (N8)	-
TP2510	-100	3.5	-1.5	125	-2.4	3-Lead SOT-89 (N8)	-
TP2520	-200	12	-0.75	125	-2.0	3-Lead SOT-89 (N8)	-
TP2522	-220	12	-0.75	125	-2.4	3-Lead SOT-89 (N8)	-
TP2535	-350	25	-0.4	125	-2.4	3-Lead TO-92 (N3)	-
TP2540	-400	25.0	-0.4	125	-2.4	3-Lead TO-92 (N3)	AN-D27
						3-Lead SOT-89 (N8)	
TP2635	-350	15	-0.7	300	-2.0	3-Lead TO-92 (N3)	-
TP2640	-400	15	-0.7	300	-2.0	3-Lead TO-92 (N3)	AN-D27
						8-Lead SOIC (LG)	
TP5322	-220	12	-0.7	110	-2.4	3-Lead SOT-23 (K1)	-
						3-Lead SOT-89 (N8)	
TP5335	-350	30	-0.4	110	-2.4	3-Lead SOT-23 (K1)	-
VP0104	-40	8.0	-0.5	60	-3.5	3-Lead TO-92 (N3)	-
VP0106	-60	8.0	-0.5	60	-3.5	3-Lead TO-92 (N3)	-
VP0109	-90	8.0	-0.5	60	-3.5	3-Lead TO-92 (N3)	-
VP0550	-500	125	-0.1	70	-4.5	3-Lead TO-92 (N3)	-
VP0808	-80	5.0	-1.1	150	-4.5	3-Lead TO-92 (L)	-
VP2106	-60	12	-0.5	60	-3.5	3-Lead TO-92 (N3)	-
VP2110	-100	12	-0.5	60	-3.5	3-Lead SOT-23 (K1)	-
VP2206	-60	0.9	-4.0	450	-3.5	3-Lead TO-92 (N3)	-
						3-Lead TO-39 (N2)	
VP2450	-500	30	-0.2	190	-3.5	3-Lead TO-92 (N3)	-
						3-Lead SOT-89 (N8)	
VP3203	-30	0.6	-4.0	300	-3.5	3-Lead TO-92 (N3)	-
						3-Lead SOT-89 (N8)	